

# Superseded



As of February 3, 2006 the Ethernet Clause 40 Auto-Crossover Conformance Test Suite version 1.7 has been superseded by the release of version 1.8. This document along with earlier versions, are available on the Ethernet Consortia test suite archive page.

Please refer to the following site for both current and superseded test suites:

<http://www.ioi.unh.edu/testsuites/ethernet/>

# **Ethernet**

## **Clause 40 Auto-Crossover Test Suite v1.7**

*Technical Document*



*Last Updated: January 30, 2006, 1:07 p.m.*

---

*Ethernet Consortium  
InterOperability Laboratory  
Research Computing Center  
University of New Hampshire*

*121 Technology Drive, Suite 2  
Durham, NH 03824  
Phone: (603) 862-0166  
Fax: (603) 862-4181*

<http://www.iol.unh.edu/consortiums/fe>  
<http://www.iol.unh.edu/consortiums/ge>

---

## MODIFICATION RECORD

- **January 30, 2006 Version 1.7**  
Matthew Hersh:
  - Added part c to test and changed discussion:
    - Test 40.1.3 – Range of sample\_timer
- **December 22, 2005 Version 1.6**  
Matthew Hersh:
  - Updated procedure for test:
    - Test 40.1.1 – Setting and Resetting of Link\_Det with Auto-Negotiation Enabled
- **December 6, 2005 Version 1.5**  
Matthew Hersh:
  - Updated discussion and observable results for test:
    - Test 40.1.4 – Implementation of A\_timer
- **June 14, 2005 Version 1.4**  
Matthew Hersh:
  - Updated observable results and possible problems for test:
    - Test 40.1.1 – Setting and Resetting of Link\_Det with Auto-Negotiation Enabled
  - Updated possible problems for test:
    - Test 40.1.2 – Setting and Resetting of Link\_Det with Auto-Negotiation Disabled
  - Updated observable results and possible problems for test:
    - Test 40.1.3 – Range of sample\_timer
  - Updated procedure for test:
    - Test 40.1.4 – Implementation of A\_timer
  - Updated discussion and observable results for test:
    - Test 40.1.5 – Maximum Channel Transmit Time
- **February 22, 2005 Version 1.3**  
Matthew Hersh:
  - Added part f and updated procedure, observable results and possible problems for test:
    - Test 40.1.1 – Setting/Resetting of Link\_Det with Auto-Negotiation Enabled
  - Updated procedure for test:
    - Test 40.1.2 – Setting/Resetting of Link\_Det with Auto-Negotiation Disabled
  - Updated observable results for test:
    - Test 40.1.3 – Implementation of A\_timer
  - Updated procedure and observable results for test:
    - Test 40.1.4 – Range of sample\_timer
  - Updated procedure for test:
    - Test 40.1.5 – Maximum Channel Transmit Time
- **December 21, 2004 Version 1.2**  
Matthew Hersh:
  - Updated procedure and observable results, and added part (e) to test:
    - Test 40.1.1 – Setting/Resetting of Link\_Det with Auto-Negotiation Enabled
  - Updated the purpose and the possible problems for test:
    - Test 40.1.4 – Range of sample\_timer
- **November 15, 2004 Version 1.1**  
Matthew Hersh:
  - Updated the observable results and possible problems for test:
    - Test 40.1.2 – Setting/Resetting of Link\_Det with Auto-Negotiation Disabled
  - Made editorial changes to procedure and observable results for test:
    - Test 40.1.3 – Implementation of A\_timer
  - Made editorial changes to the observable results for test:
    - Test 40.1.4 – Range of sample\_timer
  - Updated the discussion for test:
    - Test 40.1.5 – Maximum Channel Transmit Time
- **August 23, 2004 Version 1.0 Initial Release**

*The University of New Hampshire  
InterOperability Laboratory*

*ACKNOWLEDGMENTS*

**The University of New Hampshire would like to acknowledge the efforts of the following individuals in the development of this test suite.**

Eric Ackerson	University of New Hampshire
Milen Andonov	University of New Hampshire
Matthew Hersh	University of New Hampshire
Eric Lynskey	University of New Hampshire
Kevin McMullen	University of New Hampshire
Geoff Mitchell	University of New Hampshire

*The University of New Hampshire  
InterOperability Laboratory*

## *INTRODUCTION*

### **Overview**

The University of New Hampshire's InterOperability Laboratory (IOL) is an institution designed to improve the interoperability of standards based products by providing an environment where a product can be tested against other implementations of a standard. This suite of tests has been developed to help implementers evaluate the functioning of their Clause 22, Clause 28, and Clause 40 Auto-Negotiation based products. The tests do not determine if a product conforms to the IEEE 802.3, nor are they purely interoperability tests. Rather, they provide one method to isolate problems within an Auto-Negotiating device. Successful completion of all tests contained in this suite does not guarantee that the tested device will operate with other Auto-Negotiating devices. However, combined with satisfactory operation in the IOL's interoperability test bed, these tests provide a reasonable level of confidence that the Device Under Test (DUT) will function well in most Auto-Negotiating environments.

### **Organization of Tests**

The tests contained in this document are organized to simplify the identification of information related to a test and to facilitate in the actual testing process. Each test contains an identification section that describes the test and provides cross-reference information. The discussion section covers background information and specifies why the test is to be performed. Tests are grouped in order to reduce setup time in the lab environment. Each test contains the following information:

#### **Test Number**

The Test Number associated with each test follows a simple grouping structure. Listed first is the Test Group Number followed by the test's number within the group. This allows for the addition of future tests to the appropriate groups of the test suite without requiring the renumbering of the subsequent tests.

#### **Purpose**

The purpose is a brief statement outlining what the test attempts to achieve. The test is written at the functional level.

#### **References**

The references section lists cross-references to the IEEE 802.3 standards and other documentation that might be helpful in understanding and evaluating the test and results.

#### **Resource Requirements**

The requirements section specifies the hardware, and test equipment that will be needed to perform the test. The items contained in this section are special test devices or other facilities, which may not be available on all devices.

#### **Last Modification**

This specifies the date of the last modification to this test.

#### **Discussion**

The discussion covers the assumptions made in the design or implementation of the test as well as known limitations. Other items specific to the test are covered here.

#### **Test Setup**

*The University of New Hampshire*  
*InterOperability Laboratory*

The setup section describes the configuration of the test environment. Small changes in the configuration should be included in the test procedure.

**Procedure**

The procedure section of the test description contains the step-by-step instructions for carrying out the test. It provides a cookbook approach to testing, and may be interspersed with observable results.

**Observable Results**

The observable results section lists observables that can be examined by the tester to verify that the DUT is operating properly. When multiple values are possible for an observable, this section provides a short discussion on how to interpret them. The determination of a PASS or FAIL for a certain test is often based on the successful (or unsuccessful) detection of a certain observable.

**Possible Problems**

This section contains a description of known issues with the test procedure, which may affect test results in certain situations.

*The University of New Hampshire  
InterOperability Laboratory*

**TABLE OF CONTENTS**

<b>MODIFICATION RECORD</b>	<b>II</b>
<b>ACKNOWLEDGMENTS</b>	<b>III</b>
<b>INTRODUCTION</b>	<b>IV</b>
TABLE OF CONTENTS	VI
<b>GROUP 1: CLAUSE 40 AUTO-CROSSOVER FUNCTION REQUIREMENTS</b>	<b>1</b>
TEST #40.1.1: SETTING AND RESETTING OF LINK_DET WITH AUTO-NEGOTIATION ENABLED	2
TEST #40.1.2: SETTING AND RESETTING OF LINK_DET WITH AUTO-NEGOTIATION DISABLED	4
TEST #40.1.3: RANGE OF SAMPLE_TIMER	6
TEST #40.1.4: IMPLEMENTATION OF A_TIMER	8
TEST #40.1.5: MAXIMUM CHANNEL TRANSMIT TIME	10

## **GROUP 1: CLAUSE 40 AUTO-CROSSOVER FUNCTION REQUIREMENTS**

**Scope:** The following tests cover Auto-Negotiation operation specific to the Auto-Crossover function.

**Overview:** These tests are designed to verify that the device under test properly implements the Auto-Crossover function as it pertains to Auto-Negotiation. Auto-Crossover functions explored are defined in Clause 40 of IEEE 802.3. Many of these tests are aimed at verifying a conformant Auto-Crossover state machine implementation.

**NOTE:** THESE TESTS ARE PERFORMED FOR BOTH FAST ETHERNET AND GIGABIT ETHERNET CONSORTIUMS. THESE TESTS CANNOT BE PERFORMED IF THE DUT DOES NOT IMPLEMENT AUTO-CROSSOVER.



### **Test #40.1.1: Setting and Resetting of Link\_Det with Auto-Negotiation Enabled**

**Purpose:** To verify that the device under test properly sets, resets, and keeps Link\_Det=TRUE when Auto-Negotiation is enabled.

#### **References:**

- [1] IEEE Std 802.3, 2002 Edition: Subclauses 40.4.5.1, 40.4.5.2, and 40.4.6.2.1 *Figure 40-17 Auto-Crossover State Diagram*

#### **Resource Requirements**

- Line Monitor: A system capable of detecting and recording Fast Link Pulse bursts (FLPs) on both the receive and transmit channels of the DUT. The monitor should allow the FLPs to pass through while minimally impacting the channel.
- Traffic Generator: A system capable of generating and transmitting normal link pulses (NLPs) and fast link pulses (FLPs) while connected to the receiver of the DUT.

**Last Modification:** December 22, 2005

**Discussion:** When the DUT receives transmissions from a Link Partner, it should set Link\_Det=TRUE. The DUT should then keep transmitting on the opposite channel from the Link Partner until Link\_Det=FALSE. When sample\_timer expires without linkpulse = true or link\_status = true, it should set Link\_Det=FALSE, then begin transmissions on the opposite channel than it had been previously transmitting on. This test is designed to verify the DUT properly sets, resets, and keeps the Link\_Det variable appropriately.

**Test Setup:** Using Cat 5 cables, connect the DUT and the Traffic Generator to the Line Monitor such that the traffic generator's signaling will be seen by the DUT's receiver. Terminate the DUT's transmit channel with a 100Ω line termination.

#### **Procedure:**

##### *Part A: Reception of Alternating FLPs*

1. Enable Auto-Negotiation on the DUT.
2. Establish a connection (not a link) to the DUT.
3. Use a Traffic Generator to send the DUT FLP bursts without the ACK bit set and with alternating content for at least 20 s, such that the DUT does not enter the ACKNOWLEDGE DETECT state spaced at 16 ms apart to set Link\_Det=TRUE.
4. Observe if the DUT stays on the opposite channel from the Traffic Generator.
5. Cease transmitting FLPs.
6. Observe if the DUT begins transmitting on the channel originally occupied by the traffic generator and then continues implementing Auto-Crossover.
7. Repeat steps 1-6 on the opposite pair from step 3.

##### *Part B: Reception of Consistent FLPs*

8. Repeat part A sending FLPs with consistent content instead of FLPs with alternating content, and the Acknowledge bit not set.

*The University of New Hampshire  
InterOperability Laboratory*

*Part C: Reception of Consistent FLPs with the Acknowledge bit set*

9. Repeat steps 1 and 2.
10. Use a Traffic Generator to send the DUT enough FLP bursts with the Acknowledge bit set to put the DUT through the Complete Acknowledge state as defined in the Clause 28 State Machine Test Suite test 28.2.3 Consistency Match, part b.
11. Observe if the DUT commences transmission of link signaling on the same channel as the last transmitted FLP by the DUT.

*Part D: Reception of Next Pages*

12. Repeat part B using a Traffic Generator to send the DUT enough FLP bursts with the ACK and NP bits set and spaced at 16 ms apart to set Link\_Det=TRUE.
13. If the DUT uses an unmanaged Next Page Exchange, write a value to Register 7 to force the DUT to transmit its first Next Page.

*Part E: Reception of 10BASE-T Signaling*

14. Repeat part B sending 10BASE-T link signaling instead of FLPs.

*Part F: Reception of 100BASE-TX Signaling*

15. Repeat part B sending 100BASE-TX link signaling instead of FLPs.

**Observable Results:**

- In all cases, once the DUT has set Link\_Det=TRUE the DUT should remain transmitting on the same channel until sample\_timer expires without the DUT receiving signaling of any kind. For parts a, b, c and d if A\_timer expires immediately after sample\_timer expires between two FLPs while the DUT is transmitting in MDI-X mode, it is possible for A\_timer to force the DUT to switch back to MDI mode. This is possible if sample\_timer had just expired, and Link\_Det=FALSE. Link\_Det will remain FALSE until the first pulse of the next FLP is received. The DUT should then continue the Auto-Crossover Process. Additionally, the DUT should sustain a link for all supported speeds on both channels.
- For parts b, d, e and f, upon cessation of received signaling, the DUT should cease transmission for break\_link\_timer, and restart the Auto-Negotiation and Auto-Crossover processes.
- For part c, the DUT should enter the COMPLETE ACKNOWLEDGE state, cease FLP transmission, and begin transmitting link signaling on the opposite channel from which it was receiving. Once the DUT has commenced transmitting link signaling, the link signaling may auto-cross if no signaling is being received.

**Possible Problems:** This test cannot be performed if the DUT does not implement the Auto-Crossover function. For parts a and b, it is possible for A\_timer to expire immediately after sample\_timer expires when the DUT is transmitting in MDI-X mode. If this occurs, the DUT should switch channels to MDI mode and continue transmission of FLPs on the incorrect channel.

### **Test #40.1.2: Setting and Resetting of Link\_Det with Auto-Negotiation Disabled**

**Purpose:** To verify that the device under test properly sets, resets, and keeps Link\_Det=TRUE when Auto-Negotiation is disabled.

#### **References:**

- [1] IEEE Std 802.3, 2002 Edition: Subclauses 40.4.5.1, 40.4.5.2, and 40.4.6.2.1 *Figure 40-17 Auto Crossover State Diagram*

#### **Resource Requirements**

- Line Monitor: A system capable of detecting and recording Fast Link Pulse bursts (FLPs) on both the receive and transmit channels of the DUT. The monitor should allow the FLPs to pass through while minimally impacting the channel.
- Traffic Generator: A system capable of generating and transmitting normal link pulses (NLPs) and fast link pulses (FLPs) while connected to the receiver of the DUT.

**Last Modification:** June 14, 2005

**Discussion:** When the DUT receives supported idle transmissions from a Link Partner, it should set Link\_Det=TRUE whether or not Auto-Negotiation is enabled. The DUT should then keep transmitting on the opposite channel from the Link Partner until the link is broken. When a device detects that it has been disconnected from another device, it should set Link\_Det=FALSE, cease transmission for break\_link\_timer, then restart the Auto-Crossover process.

**Test Setup:** Using Cat 5 cables, connect the DUT and the Traffic Generator to the Line Monitor such that the DUT's receiver will see the traffic generator's signaling. Terminate the DUT's transmit channel with a 100Ω line termination.

#### **Procedure:**

##### *Part A: Reception of 10BASE-T Signaling*

1. Disable Auto-Negotiation on the DUT.
2. Establish a connection (not a link) to the DUT.
3. Use a Traffic Generator to send the DUT enough NLPs spaced at 16 ms apart to set Link\_Det=TRUE.
4. Observe whether the DUT stays on the opposite channel from the Traffic Generator.
5. Cease transmitting NLPs.
6. Observe if the DUT restarts the Auto-Crossover function.
7. Repeat steps 1-6 on the opposite pair from step 3.

##### *Part B: Reception of 100BASE-TX Signaling*

8. Repeat part A sending 100BASE-TX link signaling instead of 10BASE-T link signaling.

*The University of New Hampshire  
InterOperability Laboratory*

**Observable Results:**

- **INFORMATIVE:** In all cases, once the DUT has set Link\_Det=TRUE the DUT should continue transmitting on one channel only until link is broken. The DUT should then restart the Auto-Crossover Process. Also, the DUT should sustain a link for all supported speeds on both channels.

**Possible Problems:** This test cannot be performed if the DUT does not implement the Auto-Crossover function when Auto-Negotiation is disabled, or if the DUT does not have settings to disable Auto-Negotiation and set certain speeds. If the DUT does not Auto-Cross its link signaling (not required by standard), this test cannot be performed.

### **Test #40.1.3: Range of sample\_timer**

**Purpose:** To verify that the device under test transmits FLPs on a specified channel for a time within sample\_timer or a multiple of sample\_timer.

#### **References:**

- [1] IEEE Std 802.3, 2002 Edition: Subclauses 40.4.5.2, and 40.4.6.2.1 *Figure 40-17 Auto Crossover State Diagram*

#### **Resource Requirements**

- Line Monitor: A system capable of detecting and recording Fast Link Pulse bursts (FLPs) on both the receive and transmit channels of the DUT. The monitor should allow the FLPs to pass through while minimally impacting the channel.

**Last Modification:** June 14, 2005

**Discussion:** When a device is within the MDI mode or the MDI-X mode states and A-timer has not expired, it should stay within that state for a multiple of sample\_timer. The acceptable range is defined to be  $62 \pm 2$  ms. Since there are 11 bits within the Linear Feedback Shift Register (LFSR), the DUT could possibly transmit on one channel for any multiple of sample\_timers up to 11.

**Test Setup:** Using a Cat 5 cable, connect the DUT and the Line Monitor such that the DUT's signaling will be seen by the Line Monitor. Terminate the DUT's transmit channel with a 100 $\Omega$  line termination.

#### **Procedure:**

*Part A: Timer Within Acceptable Range Channel A*

1. Enable Auto-Negotiation on the DUT.
2. Establish a connection (not a link) to the DUT.
3. Measure the duration of transmission of FLP bursts on the DUT's MDI mode.

*Part B: Timer Within Acceptable Range Channel B*

4. Repeat step 3 on the DUT's MDI-X mode.

*Part C: Occurrences of sample\_timer*

5. Repeat step 3 on the DUT's MDI and MDI-X modes.

#### **Observable Results:**

- a. While in Auto-Crossover mode, the lowest observed duration the DUT should transmit FLPs while in MDI mode is  $62 \pm 2$  ms.
- b. INFORMATIVE: While in Auto-Crossover mode, the lowest observed duration the DUT should transmit FLPs while in MDI-X mode is  $62 \pm 2$  ms provided A\_timer has not expired.
- c. While in Auto-Crossover mode, the DUT should transmit for all possible multiples of sample\_timer.

*The University of New Hampshire*  
*InterOperability Laboratory*

**Possible Problems:** Often times an exact value of `sample_timer` cannot be determined because `sample_timer` may not always expire at the same time as `transmit_link_burst_timer`. Therefore, the observed duration of FLP transmission on a single channel may vary as `sample_timer`  $\pm$  `transmit_link_burst_timer`. If an exact value of `sample_timer` cannot be determined, this test will result in a Refer to Comments. Also, this test cannot be performed if the DUT does not implement the Auto-Crossover function.

#### **Test #40.1.4: Implementation of A\_timer**

**Purpose:** To verify that the device under test properly implements A\_timer.

#### **References:**

- [1] IEEE Std 802.3, 2002 Edition: Subclauses 40.4.5.2, and 40.4.6.2.1 *Figure 40-17 Auto Crossover State Diagram*

#### **Resource Requirements**

- Line Monitor: A system capable of detecting and recording Fast Link Pulse bursts (FLPs) on both the receive and transmit channels of the DUT. The monitor should allow the FLPs to pass through while minimally impacting the channel.

**Last Modification:** December 6, 2005

**Discussion:** A\_timer is an asynchronous (to the Auto-Crossover State Machine) free-running timer that provides for a relatively arbitrary reset of the state machine to its initial state. This timer is used to reduce the probability of a lock-up condition where both the DUT and its link partner have the same identical seed initialization at the same point in time. During the Auto Crossover process, when A\_timer or a multiple of A\_timer expires and A\_timer\_done is set to TRUE, the DUT should restart the Auto-Crossover process, reverting to the MDI channel and restarting sample\_timer.

**Test Setup:** Using a Cat 5 cable, connect the DUT and the Line Monitor such that the DUT's signaling will be seen by the Line Monitor. Terminate the DUT's transmit channel with a 100Ω line termination.

#### **Procedure:**

##### *Part A: Range of A\_timer*

1. Enable Auto-Negotiation on the DUT.
2. Establish a connection (not a link) to the DUT.
3. Monitor a significant number of FLP transmissions.
4. Search for two transmissions of FLPs on the MDI-X channel that are less than sample\_timer long.
5. Measure the time from the end of the first FLP transmission to the beginning of the second FLP transmission.
6. Verify that the spacing between the two transmissions is within the range of A\_timer.
7. Verify that the DUT uses more than one value of A\_timer.

##### *Part B: Implementation of A\_timer\_done=TRUE*

8. Make sure that on the MDI channel, FLPs are occasionally transmitted for longer than sample\_timer, and on the MDI-X channel, FLPs are occasionally transmitted for less than sample\_timer.
9. Make sure that FLPs are always transmitted on the MDI channel for at least sample\_timer.

*The University of New Hampshire  
InterOperability Laboratory*

**Observable Results:**

- a. The DUT's A\_timer should be within the range of  $1300 \pm 325$  ms.
- b. The DUT should revert to the MDI channel anytime A\_timer\_done=TRUE whether or not sample\_timer has expired. (Sometimes in the middle of an FLP.) Also, if already transmitting on the MDI channel, and the DUT resets its sample\_timer, the result of this would be a transmission of longer than sample\_timer on the MDI channel.

**Possible Problems:** This test cannot be performed if the DUT does not implement the Auto-Crossover function.



### **Test #40.1.5: Maximum Channel Transmit Time**

**Purpose:** To verify that the device under test transmits FLPs on a certain channel for less than the maximum of 704 milliseconds.

#### **References:**

- [1] IEEE Std 802.3, 2002 Edition: Subclauses 40.4.4.2, 40.4.5.2, and 40.4.6.2.1 *Figure 40-17 Auto-Crossover State Diagram*

#### **Resource Requirements**

- Line Monitor: A system capable of detecting and recording Fast Link Pulse bursts (FLPs) on both the receive and transmit channels of the DUT. The monitor should allow the FLPs to pass through while minimally impacting the channel.

**Last Modification:** June 14, 2005

**Discussion:** When a device is within the MDI mode or the MDI-X mode states, it should stay within that state for no longer than 704 ms. A device is required to remain on one channel for a minimum of  $62 \pm 2$  ms., thus the maximum of `sample_timer` is 64 ms. Since there are 11 bits within the Linear Feedback Shift Register (LFSR), the DUT could possibly transmit on one channel for up to 11 `sample_timers`, which yields a maximum of (64 ms X 11 bits), or 704 ms, for the maximum amount of time a device can transmit on one channel.

**Test Setup:** Using a Cat 5 cable, connect the DUT and the Line Monitor such that the DUT's signaling will be seen by the Line Monitor. Terminate the DUT's transmit channel with a 100 $\Omega$  line termination.

#### **Procedure:**

*Part A: Timer Within Acceptable Range Channel A*

1. Enable Auto-Negotiation on the DUT.
2. Establish a connection (not a link) to the DUT.
3. Measure the duration of transmission of FLP bursts on the DUT's MDI mode.

*Part B: Timer Within Acceptable Range Channel B*

4. Repeat step 3 on the DUT's MDI-X mode.

#### **Observable Results:**

- While in Auto Crossover mode, the maximum amount of time the DUT should transmit FLPs in MDI mode is 768 ms. The DUT may transmit on one channel for up to 704 ms, however, if `A_timer` expires after the DUT has transmitted for 11 `sample_timers`, it will transmit for a maximum of one additional `sample_timer` in MDI mode.
- While in Auto Crossover mode, the maximum amount of time the DUT should transmit FLPs in MDI-X mode is 704 ms.

**Possible Problems:** This test cannot be performed if the DUT does not implement the Auto-Crossover function.